

ELECTRICAL RESEARCH AND DEVELOPMENT ASSOCIATION

ERDA Road, Makarpura Industrial Estate, Vadodara-390 010, India.

EPABX: +91 (0265) 2642942, 2642964, 2642377, 3043128 / 29 / 30 / 31 / 33,

Fax : +91 (0265) 2638382,

E-mail : erda@erda.org

Web : http://www.erda.org




TEST REPORT

Sheet 1 of 3

NAME & ADDRESS OF CUSTOMER M/s. VOLTECH MANUFACTURING COMPANY LIMITED. NO.2/431-B, SRI KUMARAN NAGAR, KUNDRATHUR, CHENNAI - 600128.	REPORT NO. : RP-1617-003385 DATE : 23.04.2016	
	CUSTOMER REF. NO.: Letter dtd.18.04.2016 and E mail dtd. 23.04.2016	
	DATE OF SAMPLE RECEIPT -----	DATE OF TESTING 22.04.2016
SAMPLE DESCRIPTION 220V 100A FLOAT CUM BOOST BATTERY CHARGER Input voltage: 415±10% AC.V & 50 Hz±5% frequency variation, 3-phase, 3-wire system, Output voltage : nominal voltage : 220V DC, float voltage :247, boost voltage : 255V DC, DC current : 100A, Type: SCR-Full wave Fully controlled, No. of Pulse : SCR Thyristor - 6 Pulse, Regulation:≤1%@±10% input voltage, ±5% frequency with 0 to 100% load variations, Efficiency: ≥ 80% @ full load, Ripple:≤2% @ Full load (Without connecting battery), Cooling : Air Natural, Insulation : Class F, IP Protection :IP 42, Serial No.: VMC-04-16-FCBC-341.	SAMPLE IDENTIFICATION WO-1617-000880-1	
TEST DETAILS 1. Voltage Regulation. 2. Ripple factor (With resistive load) 3. Efficiency test (At full load)	TEST SPECIFICATION As per customer's requirement As per customer's requirement. As per customer's requirement.	
ENCLOSURES : Photograph Nos.: WO-1617-000880/1 to 3. REMARKS : As per attached sheet.		
 PREPARED BY	 CHECKED BY	 APPROVED BY (Gautam Brahmhatt)
Note : 1. This report relates only to the particular sample received for testing in good condition at M/s. Voltech Manufacturing company Limited., Chennai. 2. This report cannot be reproduced in part under any circumstances. 3. Publication of this report requires prior permission in writing from Director, ERDA. 4. Only the tests asked for by the customer have been carried out. 5. In case of any dispute, Vadodara will be the exclusive jurisdiction & shall be construed as where the cause has arised. Caution : ERDA is not responsible for the authenticity of photocopied or reproduced test reports. ERDA provides support to customers for verification of the authenticity of test reports issued by ERDA.		

1557669



ELECTRICAL RESEARCH AND DEVELOPMENT ASSOCIATION

ERDA Road, Makarpura Industrial Estate, Vadodara-390 010, India.

EPABX: +91 (0265) 2642942, 2642964, 2642377, 3043128 / 29 / 30 / 31 / 33,

Fax : +91 (0265) 2638382,

E-mail : erda@erda.org

Web : http://www.erda.org



Report No.: RP-1617-003385

Date:23.04.2016

Sheet 2 of 3

Sr. No.	Particulars of test and clause no.	Requirement as per specification.	Obtained value	Remarks
1.	Voltage Regulation. [As per customer's requirement]	Less than 1% @ $\pm 10\%$ input voltage with 0 to 100% load variations. [Declared by customer]	0.68%	Conforms
2.	Ripple factor (With resistive load) [As per customer's requirement]	Less than 2% with resistive load. [Declared by customer]	0.58%	Conforms
3.	Efficiency test (At full load) [As per customer's requirement]	$\geq 80\%$ at full load [Declared by customer]	82.0%	Conforms

Note: The detail of measurement data for above three tests as per sr. no. 1 to 3 is given in Table 1, Table 2 and Table 3 respectively at Page 3 of 3.

Master Equipment and Calibration Details traceable to NPL

(National Physical Laboratory), New Delhi.

Sr. No.	Test Equipment	ERDA SR. NO.	Calibration status (Valid up to)
1	6 ^{1/2} Digit Multimeter	8108	12.10.2016
2	Clamp On Power meter	7140	03.12.2016
3	Clamp On tester	10204	09.01.2017

Caualy

PREPARED BY

[Signature]

CHECKED BY



1557668

ELECTRICAL RESEARCH AND DEVELOPMENT ASSOCIATION

ERDA Road, Makarpura Industrial Estate, Vadodra-390 010, India.

EPABX: +91 (0265) 2642942, 2642964, 2642377, 3043128 / 29 / 30 / 31 / 33,

Fax : +91 (0265) 2638382,

E-mail : erda@erda.org

Web : http://www.erda.org



Report No.: RP-1617-003385

Date:23.04.2016

Sheet 3 of 3

Table 1 [Regulation]

Sr. No.	AC INPUT VOLTAGE (V)			DC OUTPUT VOLTAGE (V)	OUTPUT CURRENT (A)	REGULATION (%)
	RY	YB	BR			
BOOST VOLTAGE 255V @ -10% INPUT VOLTAGE						
1	373.5	376.8	378.0	255.17	0.0 0	0.68 %
2	372.1	376.8	377.0	253.45	100.0	
BOOST VOLTAGE 255V @ NOMINAL INPUT VOLTAGE						
3	413.0	417.6	417.3	255.26	0.0 0	0.08 %
4	412.2	418.2	417.8	255.05	100.0	
BOOST VOLTAGE 255V @ +10% INPUT VOLTAGE						
5	453.5	457.8	458.3	255.02	0.0 0	0.05 %
6	442.7	448.9	448.2	254.90	100.0	

Table 2 [Ripple]

Peak to Peak voltage (V Pk-Pk)	DC voltage at Full Load (V DC)	Ripple factor (%)
4.218 V	254.95	0.58 %

Table 3 [Efficiency]

AC Input Voltage (V)	AC Input Current (A)	Input Power (W)	DC Output Voltage (V)	DC Output Current (A)	DC Output Power (W)	Efficiency (%)
RY	411.9	31101.0	255.13	100.0	25513.0	82.0
YB	419.1					
BR	418.4					

1557664

Analy

PREPARED BY

[Signature]

CHECKED BY



